

The dimensions below are approximate cable diameters. Variation in production may result in slight differences. Cable configuration is found on page 4 of the pump data pack.

### Non-FM Cable (RHW-2)

Cable Size	Jacket OD (mm)	Jacket OD (in)
14AWG-4 + 14AWG-4	20	0.79
12AWG-4 + 14AWG-4	22	0.87
10AWG-4 + 14AWG-4	30	1.18
8AWG-4 + 14AWG-4	31	1.22
6AWG-4 + 14AWG-4	32	1.26
4AWG-4 + 14AWG-4	33	1.30
3AWG-4 + 14AWG-4	34	1.34
16AWG-12	18	0.71
14AWG-4	14.5	0.57

### FM Cable (H07RN8-F Plus)

Cable Size	Jacket OD (mm)	Jacket OD (in)
4G1.5	11	0.43
5G1.5	12	0.47
6G1.5	14	0.55
7G1.5	16	0.62
7G2.5	18	0.7
7G4	22	0.86
10G1.5	19	0.74
10G2.5	21	0.82
10G4	24	0.94
5G6	19	0.74
4G2.5	13	0.5
4G4	16	0.6
4G6	18	0.7
4G10	23	0.9
4G16	28	1.09
4G25	32	1.25
4G35	34	1.34

Non-FM (RHW) cable specification is given as:

(power leads in AWG) – (qty. of power leads) + (control leads in AWG) – (qty. of control leads)

FM (H07RN8-F Plus) cable specification is given as:

(qty. of leads) G (size of leads in sq. mm)